

Desktop Reader Come With Build-in RS485 Converter USB Connection to PC

**PS21- Smartcard (13.56MHz)
Proximity (125KHz)**

USB300C/D

Integrated USB to Rs485 convertor and card register.



Introduction

USB300 is design for simple added card and connected access security system with pc server.
Use USB300, you can add card No. to every windows software (include access security system); USB 300 use usb technique, you can easy connect access security system with pc;

Feature

USB technique.

Achieve USB to Rs485 convert, easy to connect access security network to pc server.

Builed into card register, USB300D can read ID card, USB300C can read IC card and USB300CWR can read and write IC card.

RS485 network port protect with Current-Limiting and Driver Overload Protection

Electrical Characteristics	
Operating Voltage Range:	5VDC (from USB port supply)
USB format	USB1.1
Built-in USB to RS-485 convertor	Connector is RJ45
Built-in Card Reader (USB300D)	
Modulation	ASK at 125KHz (Proximity)
Compatiable Cards	All 26-Bit 125KHz (Proximity)125KHz (Proximity)
USB300C	
Modulation	13.568MHz
Compatiable Cards	ISO/IEC 14443A, MIFARE @ Classic and MIFARE @Pro
USB300CWR	
Modulation	13.568MH
Compatiable Cards	ISO/IEC 14443A, MIFARE @ Classic and MIFARE @Pro Banks read and write
Operating Temperature Ranges:	-25C to 75C
Dimensions:	90mm L* 90mm W* 35mm D

EcoGreen @sg

Address: Blk. 153 Bukit Batok St.11 # 03-296, Singapore 650153 | Website: www.ecogreen@sg

